

MITSUBISHI MGS SERIES

DIESEL GENERATOR SET


50Hz/1500 rpm/10kV



MGS2700HV

50Hz/10kV

POWER RATING (0.8 P.F.)		MODEL CODE
STAND-BY	2500 kVA	50S-P629
PRIME	2250 kVA	50P-P629



MGS2700HV with typical options

CONDITIONS & DEFINITIONS

Stand-by: Code: S

Applicable for supplying emergency power at varying load in the event of normal utility power interruption.

Fuel stop power in accordance with ISO15550, ISO3046/1, JISB8002-1, DIN6271 and BS5514.

Prime: Code: P

Applicable for supplying power to a constant electrical load for limited hours.

Limited-Time Running Power (LTP) in accordance with ISO8528.

Conditions:

Engine ratings are based on SAE J1349 standard conditions and also apply at ISO3046/1, DIN6271 & BS5514 standard conditions.

Fuel rates: based on ASTM D975, BS2869 and on fuel oil of 35° API (16°C or 60° F) gravity having a LHV of 42,780 kJ/kg (18,390 Btu/lb.) when used at 29°C (85° F) and weighing 838.9 g/liter (7.001 lbs./U.S. gal.).

DIMENSION (Reference Data)

			STAND-BY	PRIME
			2500 kVA	2250 kVA
Overall dimensions	L : Length	mm	6985	6985
	W : Width	mm	2825	2825
	H : Height	mm	3365	3365
Total Weight (Dry)		kg	20100	20100
Total Weight (Wet)		kg	21100	21100

MITSUBISHI MGS SERIES

DIESEL GENERATOR SET
MGS2700HV



MGS SERIES DIESEL ENGINE: MITSUBISHI S16R2-PTAW

V-16, 4 stroke-cycle water-cooled, turbocharged and aftercooled

ENGINE SPECIFICATIONS & TECHNICAL DATA

Bore	mm	170
Stroke	mm	220
Displacement	L	79.9
Piston speed	m/sec.	11.0
Compression ratio		14
Lubricating oil capacity	L	290
Coolant capacity without radiator	L	190
Coolant pump external resistance	m water	5.0
Coolant pump flow rate	L/min	1650
Cooling fan airflow rate	m ³ /min	2760
Cooling fan air flow restriction	kPa	0.1
Ambient air temperature	°C	40
Allowable exhaust back pressure	kPa	6.0
Exhaust flange size (internal diameter)	mm	350

ENGINE OPERATING DATA

		STAND-BY	PRIME
		2500 kVA	2250 kVA
Gross Engine Power*	kWm	2110	1903
Brake mean effective pressure	MPa	2.16	1.95
Regenerative absorption	kW	152	152
Noise Level at 1 m (excluding: intake, exhaust & fan)	dB(A)	130	128
Fuel consumption load 100%*	L/hr.	532	476
Fuel consumption load 75%*	L/hr.	404	364
Combustion air inlet flow rate	m ³ /min	182	163
Exhaust gas flow rate	m ³ /min	481	430
Exhaust gas temperature	°C	530	520
Heat rejection to coolant	kW	822	735
Heat rejection to exhaust	kW	1454	1285
Heat rejection to atmosphere from engine	kW	159	142
Heat rejection to atmosphere from generator	kW	103	93

* WITH FAN basis.

Deration for engine

Note: Please consult with your nearest Mitsubishi MGS dealer

ENGINE STANDARD EQUIPMENT

Aftercooler
Turbocharger filter
Structure steel base
Crankcase breather
Charging alternator
Lubricating oil cooler
Fuel filters, full flow paper element
Fuel transfer pump, gear driven, plunger type
Electronic type governor
Jacket water heater
Jacket water pump, gear driven
Lubricating oil filter, full flow paper element
Lubricating oil pump, gear driven
Exhaust dry manifold
Radiator, blower fan, fan drive
Manual shutoff
24V DC electric starting motor

MITSUBISHI MGS SERIES

DIESEL GENERATOR SET
MGS2700HV



MGS SERIES 7310 GENERATOR CONTROL PANEL

Type & Design

MGS standard 7310 programmable microprocessor control-automatic start/stop panel, generator breaker control, indicating the operational status and fault conditions; automatically shutting down the engine and indicating the engine failure by means of LCD display and LEDs on the front panel.

Controls & Monitoring

- ◆ Mode selection & start engine button with interlock key switch system
- ◆ Menu navigation button
- ◆ LCD display for: AC amperage-each phase and earth current, AC voltage-each phase and neutral, Frequency Hz, Operation hours run, Lub. Oil pressure, Lub. Oil Temperature, DC Battery Voltage, Cooling water temperature, Generator Load kW/kVA/kVar, Generator Load kWh/kVAh/kVarh
- ◆ Operation status LED indicators
- ◆ CB control buttons
- ◆ Mute/Lamp test button
- ◆ Voltage adjuster
- ◆ Speed adjuster
- ◆ Emergency stop pushbutton
- ◆ Provided 5 outputs for status as standard equipment (Programmable 8 outputs available as option)

Safety Shutdown Protection

High engine temperature, Low oil pressure, Fail to start, Generator Over Speed/Frequency, Coolant high temperature, Generator Under Speed/Frequency, Generator High Voltage, Generator Low Voltage, Oil pressure sender circuit, Loss of Speed signal, Emergency stop.

Mounting

Fabricated cubicle mounted on individual bracket with anti-vibration isolator

Electrical Design

In accordance with BS EN 60950 Low Voltage Directive, BS EN 61006-2 and 61006-4 EMC Directive. The optional interface can provide real time diagnostic facilities.

Generator Control Panel Description

- 3 position operation mode control key switch (ACTIVE, PANEL LOCK, STOP/RESET)
- Manual button
- Auto button
- CB open button (Manual only)
- CB close button (Manual only)
- Start engine button (Manual only)
- LCD display accessed by scroll pushbutton
 - Generator volts L1-N, L2-N, L3-N
 - Generator volts L1-L2, L2-L3, L3-L1
 - Generator amps L1, L2, L3
 - Generator Earth Current
 - Generator Frequency Hz
 - Engine speed RPM
 - Engine oil pressure (PSI & Bar)
 - Engine cooling water temperature (°C & °F)
 - Battery volts
 - Engine hours run
 - Generator Load kW, kVA, kVar
 - Generator Load kWh, kVAh, kVarh
 - Power Factor
- Visual indicators on LCD display
 - Shutdown alarm
 - Warning alarm
 - High coolant temperature
 - Low oil pressure
 - Charge fail
 - Over-speed
 - Under-speed
 - Electrical trip
 - Fail to stop
 - Generator high current
 - Over voltage (AC)
 - Under voltage (AC)
 - Over voltage (DC)
 - Under voltage (DC)
 - Auxiliary indication
 - Auxiliary alarm (warning or shutdown)
 - Common alarm
 - Over frequency
 - Under frequency
- Visual indication alarm and automatically shutdown
 - High engine temperature
 - Low oil pressure
 - Fail to start
 - Over-speed
 - High voltage
 - Low voltage
 - Over frequency
 - Under frequency
 - Oil pressure sender open circuit
 - Loss of speed signal
 - High Crankcase internal pressure (MGS-C Continuous only)
 - Emergency Stop
- Operation status indicated by LED
 - Remote start present
 - Generator ready
 - Lubrication oil filter clogged
 - Electrical trip
- Pre-Programmed Starting Unit
 - Automatic start/stop sequence timing and delay systems configured via MS-Windows based software.

MITSUBISHI MGS SERIES

DIESEL GENERATOR SET
MGS2700HV



MGS SERIES AC GENERATOR MODEL: MG-KP629

Type & Design

MGS original design, double bearings, 4 pole, screen protected, selfexciting, self regulating and brushless with fully connected damper windings, salient pole rotors, A.C. exciter and rotating rectifier unit. Direct coupled to engine and regreaseable bearing, direct drive centrifugal blower.
With space heater.

Enclosure: Drip-proof IP22
Terminal box: Totally enclosed IP44

Winding System

Standard 6 wire winding is provided. All windings are formed wound and impregnated in vacuum pressure with a special epoxy resin.

Overspeed capability: 125% for 2 minutes
Insulation: Class 'F' of IEC
Temperature rise: 130°C (Stand-by)
Temperature rise: 105°C (Prime)

Voltage Regulator

Fully sealed, 3 phase RMS sensing AVR with built-in protection against sustained over-excitation. This de-excites the generator after a minimum of 5 seconds.

Voltage regulation: Less than +/- 0.5% from no load to full load at any power factor between 0.8 lagging and 1.0 allowing for a 4% engine speed variation

Voltage adjustment: +/- 6%
Wave form: Less than 5% deviation

Permanent Magnet Generator (PMG)

Electrically isolated from the main alternator stator windings powers AVR - sustaining approx. 250% of short circuit current at the AC generator output terminals for not more than 10 seconds by means of excitation voltage via AVR

Sensors

Temperature sensors are provided as follows.
Stator winding, 2 per each phase, PT100
Bearing, 1 per each bearing, PT100

Electrical Design

In accordance with BS5000 Part 3, VDE0530, UTE51100, NEMA MG1-22, CEMA, IEC34-1, CSA22.2, AS1359 and JEC2100.

Telephone Influence Factor (TIF): Less than 50
Telephone Harmonic factor (THF): Less than 2.5%
Radio interference: Suppression is in line with the provision of VDE Class G and N

Gen Set Option Features

- | | |
|-------------------------------------|---|
| ■ ENGINE | ■ GENERATOR |
| Air Cleaner, paper element dry type | Power Factor Regulator |
| Battery Kit | ■ CONTROL PANEL |
| Battery Charger | Diesel Generator Integrated Communication Synthesizer (DGICS-MII) |
| Anchor Bolts | Auxiliary Control Panel |
| ■ FUEL | Remote Monitor Interface |
| Fuel Day Service Tank | Temperature Meter for Winding & Bearing |
| ■ LUBRICATION | ■ SWITCHGEAR |
| Lub. Oil Priming Pump | Circuit Breaker VCB |
| ■ EXHAUST | Reverse Power Relay |
| Exhaust Silencer | |
| Exhaust Flexible Pipe | |



Power Systems Engine Section, Engine Sales Department
16-5, KONAN 2-CHOME, MINATO-KU, TOKYO 108-8215 JAPAN
TEL: 81-3-6716-4771 FAX: 81-3-6716-5854

Mitsubishi Heavy Industries, Ltd. serves for the customers with improved products continually.
Therefore specification and some materials will be changed without notice.
The International System of units (SI) is used in this publication.

